

## FLOODLINE Remote Alarm Unit



The Floodline Remote Alarm unit provides a visual and audible warning of a leak or even a system fault.

The Remote Alarm is available as an industrial design in a surface-mounted ABS box or as flush-mounted brushed chrome version for areas which require the device to integrate into the decor.

It can be mounted anywhere within the building and is connected back to the main Floodline Control Panel.

For example, the main control panel may be mounted in the security office but some form of repeat indicator is needed at the reception desk which is manned 24hrs.

### Function:

Remote alarm alert of main control panel status.

### Power:

12VDC, 37mA fed from main panel.

### Construction:

ABS Plastic enclosure for internal use only or brushed chrome face plate for a 2-gang electrical socket.

### Dimensions:

H85 x W142 x D57 mm (ABS version)  
H88 x W148 mm (2-gang faceplate)

### Fixing:

Wall/surface mounted.

### Alarm Indicators:

Flashing red LED for LEAK or SYSTEM FAULT (all alarms displayed continuously until corrected and reset at main control panel) audible alarm.

### Controls:

Keyswitch mute (ABS version)  
Push switch mute (2-gang faceplate)  
Auto Reset - resets when main panel is reset.

Other, non-standard remote alarm units can be supplied to specific requirement.

We can also provide other communication options including AUTODIALLERS and DIGITAL Communicators. We would be pleased to discuss your requirements.

